

BUZZSTOP-MKIII

Universal signal convertor & ground isolator



The BUZZSTOP-MKIII is a universal input adaptor that can be used for all connections and extensions. The input level selector allows you to convert any amplifier output to any line-level output, balanced or unbalanced. (E.g.: You can convert a 100V loudspeaker signal into a balanced or unbalanced line level signal). The BUZZSTOP-MKIII also makes it possible to convert an unbalanced signal into balanced and vice versa.

A 19" adaptor set is available. This way it is possible to mount 2 BUZZSTOP-MKIII in a 19" rack. (REF: BUZZ-19)

Often the BUZZSTOP-MKIII is used to solve humm and buzz problems via the build-in audio transformer. This can be a perfect way to avoid ground loops.

TECHNICAL SPECIFICATIONS

inputs - line level - balanced	Euroblock, 0dB-1V	inputs - line level - unbalanced	RCA cinch, 0dB-1V
inputs - high level - PA amp	Euroblock, 100V-70V-33V	inputs - high level - low imp amp	8 Ohm & 1kW-600W-120W
inputs - high level - telephone	Euroblock	outputs - balanced	Euroblock, Line 0dB-1V
outputs - unbalanced	RCA cinch, 0dB-1V	width in mm	241
height in mm	44	depth in mm	72
weight in gr	500	Net weight product (kg)	0,50

MORE PICTURES

