

## TECHNICAL SPECIFICATIONS



### iLive 2x2 receiver

**iLive 2X2 dual channel wireless receiver with 32 selectable channels and automatic channel targeting.**

These universal dual channel receivers can be combined with handheld microphone or body pack transmitter together with lavalier or headset microphone. iLive 2X2 receivers can be used with all iLive 2 series hand held transmitters and body packs.

	<b>iLive 2X2 receiver</b>
Carrier frequency range	606 MHz - 634,4 MHz
Power supply	12-15 V DC, 1.25 A
Output	Balanced XLR , unbalanced 6,3 mm TS JACK
Receiver way	Two frequency conversion super-heterodynes
Intermediate frequency	10,7 MHz
Antenna	BNC
T.H.D	< 0,7 %
Sensitivity	6 dB $\mu$ V
Image rejection	36 dB
Max. audio output	0 dB
Dimensions (H x W x D)	45 mm x 210 mm x 206 mm
Weight	1.4 kg
Material	Steel enclosure, aluminum front panel