

# PM1122RL

Wall control panel with local input  
for PM1122



The PM1122RL is a very affordable remote control panel with local audio input (mini-jack and XLR) for the PM1122 multifunctional pre-amplifier.

The control panel offers music level control, line source selection and microphone mix level control. The PM1122RL also adds a double local source input, which means that there can be a microphone on the XLR and/or an MP3 player, or a pc or other line input on the stereo mini-jack connector.

However, the local source input is always mono. There can be phantom power to the XLR connector by setting a jumper on the pack of the control panel.

The remote panels are connected to the PM1122 by a standard CAT-5 cable wired according to the T-568B protocol. The maximum wire length is up to 300m, according to circumstances. You can use one PM1122RL per zone. Mounting screws are included.

## TECHNICAL SPECIFICATIONS

display	No	display backlight	No
supported main unit	PM1122	programmable functions	No
addressing	Hardwired	connector type	RJ45
max. cable length in m	300	power type	Phantom
inputs	Bal. Mic. & Unbal. Line	width in mm	115
height in mm	115	depth in mm	40
weight in gr	260	Net weight product (kg)	0,25

MORE PICTURES



## ACCESSORIES



**BBI2**

Universal BTicino built-in box 2 x 3 modules



**BB2**

Build on box for remote panel with input PM1122RL, white