

PTZOptics

Introducing the new SuperJoy Joystick Controller supporting Network and Serial Camera Control. Experience the full capabilities by pairing it with PTZOptics or HuddleCamHD cameras.

Main Features

- Durable metal housing
- PTZOptics VISCA over IP & Serial control
- Limited NDI & Sony control
- PTZOptics Camera On Screen Display control
- Full Pan / Tilt / Zoom camera control
- PTZ, Focus, and Preset Speed Adjustment on the fly
- 4 Camera Control Groups
 - 7 Cameras per Camera Group
- 255 camera presets, 9 Quick presets
- 4 Customizable buttons (TCP, UDP, & HTTP)
- Fine tune zoom & focus control dials
- Buttons glow / flash when available
- RTSP Decoder via HDMI
- PTZOptics Focus Lock & Unlock
- Large LCD screen with controller status
- Import / Export settings via network & USB
- 2-Year warranty

Model Number: PT-SUPERJOY-G1

What's in the box?

- PT-SUPERJOY-G1 Joystick Controller
- 12V 2A DC International Power Supply
- RS-232C | DB9 to 8-pin mini-din cable
- PT-SUPERJOY-G1 Quick Start Guide



Technical Specifications	
Connections	RS-232, RS-485, RS-422, RJ-45
Control Protocols	VISCA, VISCA over IP, PELCO-D, PELCO-P, Sony, & NDI
Max Cameras	28 cameras total (4 groups of 7 channels)
Recommended Max Distance	RS-232 / RS-422: 50 ft 15m RS-485: 3,937 ft 1200m Ethernet: 328 ft 100m
Baud rate	1200 ~ 19200 bps

Operation Specifications	
Power	6W 12VDC / PoE (802.3af) (Only use one (1) power source at a time.)
Working Temp	14° F ~ 122° F -10° C ~ +50° C
Working Humidity	10% ~ 90% (non-condensation)
Weight	3.75 lbs 1.70 kg
Dimensions (in.)	13.94 W x 7.05 D x 3.98 H
Dimensions (mm.)	370 W x 180 D x 101 H