

T20IP

waterproof 8 ohms / 100 volt transformer, 20 watts



The T20IP is a small built-in 100 volt line transformer, designed to make it possible to convert a standard 8 ohms loudspeaker into a 100 volt line speaker with selectable power taps (2.5 – 5 – 10 and 20 watts in 100 volt).

This transformer will open a lot of additional speaker models to the 100 volt speaker range. The only thing that needs to be done is to connect the T20IP transformer between the 100 volt amplifier and the low impedance loudspeaker.

Another great advantage of the T20IP is that it's packed inside a humidity resistant box.

The waterproof marine loudspeakers, the SMART Series, are already equipped with this 20 watts transformer what makes this waterproof series suited for low impedance as well as 100 volt systems.

TECHNICAL SPECIFICATIONS

height in mm	53	width in mm	112
depth in mm	58	100V transformer power taps in watts	20 - 10 - 5 - 2.5
input in ohms	8	output in volt	100
Net weight product (kg)	0,53		

MORE PICTURES

