



# CONTROL 54

## 54-CHANNEL DMX CONTROLLER

- ▶ 54-Channel DMX controller
- ▶ For up to 9 fixtures or fixture groups
- ▶ Compatible with all RGB, RGBW, RGBWA and RGBWA+UV fixtures
- ▶ 6 smooth faders for Red, Green, Blue, White, Amber and UV intensity control
- ▶ 9 colour presets with direct-access buttons
- ▶ Direct access to Auto or Manual Modes, Blackout, Colour Jump, Colour Fade, Strobe and Sound Activation with sensitivity control
- ▶ Powered by included adapter or 9 V battery
- ▶ Ideal for DJs, nightclubs, lounges, bars etc.



### SPECIFICATIONS

Product Number:	
Product Type:	DMX Mixers
Number Of DMX Channels	54
Control:	USITT DMX 512 Protocol
Features:	Auto Mode, Blackout, Colour Jump, Colour Macros, Manual Control, Stroboscope, Colour Fade, Music Control
DMX Output:	XLR 3-Pin Female
Controls:	22 Control Buttons, 6x Channel Faders, Controller For Microphone Sensitivity, On / Off Switch

Indicators:	LC Display
Operating Voltage:	External Power Supply, 9 V Block, 9 - 12 V DC
Colour:	Grey
Material:	Metal
Width:	316 mm
Height:	63 mm
Depth:	140 mm
Accessories (included):	9 V Block, Power Supply
Weight:	1.5 kg