

MA200CDR

4-zone 100V mixing amplifier with tuner and CD, 200W



MA200CDR is a 200 watts 100 volt mixing amplifier with 4 output zones with integrated AF/FM tuner and a CD/MP3 player. This professional public address system has 4 balanced microphone inputs with integrated speech filters, paging priority switch, VOX circuitry, built-in ding dong chime, three stereo and one mono line input on RCA connectors and an emergency input. Stereo line inputs are internally mixed to mono.

The output zone selectors on the front of the MA200CDR allow you to switch on/off a zone (zone 1-3) or to switch on/off music and paging for zone 4. A built-in limiter on the outputs protects your sound system and the dynamic filters on the microphone outputs contribute to high intelligibility.

MA200CDR has a combined stereo CD in or out RCA. When the internal CD player is powered off, you can connect an external line source (CD player) on these RCA's. When the internal CD player is on, the stereo signal of the CD player is available here. The unit also has mains power and emergency power connectors.

This mixing amplifier has a 3-level priority system where the emergency line / telephone input at the back has the highest priority. MIC1 has the second priority level and the third priority level can be activated by a dry contact at the back of the amplifier that mutes all background music inputs and activates the integrated chime.

TECHNICAL SPECIFICATIONS

19" (483 mm wide) rack mounting	Yes	height- rack units (1U=44 mm) in U	2
depth (build in) in mm	370	depth (incl front) in mm	386
power supply in volts	115 - 230 VAC	emergency power supply in volts output power RMS 100 volts in watts	24 VDC
power consumption (max) in	760 VA		
watts	, , , ,		200
output power RMS 8 ohms in	200		
watts		music program power in watts	240
minimum impedance load in	8	output power tappings	100 - 70 - 50 volt - 80hm
ohms		MIC inputs balanced	4
zone outputs			
to a day tale Discourse and a second		line input unbalanced	4
inputs with Phantom power	4	priority switch	1
tone control	Yes	chime	V
VOX mute	Yes	cnime	Yes
		priority output	24 VDC
emergency input	Yes	frequency response (in Hz)	40 - 25K
priority levels	3		V
tuner (AM, FM, DAB,)	Yes	CD/MP3 player (CD, MP3,) applicable in 100V	Yes
tulier (Alvi, Fivi, DAD,)	163		Yes
cooling system	fan		
applicable low impedance	Yes		



MORE PICTURES







ACCESSORIES



MICPAT-DAll call dynamic paging microphone