

# ROADBUDDY

BATTERY POWERED BLUETOOTH® LOUDSPEAKER WITH MIXER AND WIRELESS MICROPHONE

## CONNECT ALMOST ANY AUDIO SOURCE

The integrated mixer sports three channels with individual volume controls, a 2-band EQ plus adjustable echo and master volume. It delivers up to a stunning 480 watts of class D peak power and comes in 6" and 10" woofer versions.



## TAKE IT EASY

The Road Buddy speakers come with a handy IR remote control and convenient pole mount insert.



## LESS WIRE. MORE FREEDOM.

The Road Buddy incorporates an UHF receiver available with three different frequency bands (B1: 863 - 865 Mhz // B5: 584 - 607 MHz // B6: 655 - 679 MHz) and features a slot for an additional unit available as accessory. It comes with a choice of handheld or headset wireless microphones.



## VERSATILE MEDIA PLAYER

A major Road Buddy feature, the built-in Bluetooth® player also supports USB storage devices and SD cards and includes multiple genre specific presets for instant EQ adjustment.



## READY FOR TAKE OFF

A rechargeable battery pack provides up to 8 hours of continuous operation. With built-in wheels and extension handles for carting convenience the Road Buddy active 2-way systems take your sound everywhere.



ALSO AVAILABLE  
WITH HEADSET MICROPHONE.

**WIRELESS MICROPHONE AVAILABLE  
WITH THREE FREQUENCY RANGES:**

Standard: 863 - 865 MHz  
B5: 584 - 607 MHz  
B6: 655 - 679 MHz

**ROADBUDDY 10 (B5,B6)**

BATTERY POWERED BLUETOOTH LOUDSPEAKER  
WITH MIXER AND WIRELESS MICROPHONE



**LDRBUD10BPH2 (B5,B6)**

BATTERY-POWERED BLUETOOTH SPEAKER  
WITH MIXER, 2 BODYPACK AND 2 HEADSETS



**LDRBUD10HHD2 (B5,B6)**

BATTERY-POWERED BLUETOOTH SPEAKER  
WITH MIXER AND 2 WIRELESS MICROPHONES



**LDRBUD10HBH2 (B5,B6)**

BATTERY-POWERED BLUETOOTH SPEAKER  
WITH MIXER AND WIRELESS MICROPHONE

# ROAD SERIES

## PORTABLE BATTERY POWERED ACTIVE PA SPEAKERS

### SPECIFICATIONS ROADBUDDY:

|                                |                                                                                                          |
|--------------------------------|----------------------------------------------------------------------------------------------------------|
| Art. No.:                      | LDRBUD10(HS)                                                                                             |
| Product type:                  | Portable PA speaker                                                                                      |
| Type:                          | active                                                                                                   |
| Low/mid driver dimensions:     | 10"                                                                                                      |
| Woofers magnet:                | Ferrite                                                                                                  |
| Woofers brand:                 | Custom-made                                                                                              |
| HF driver dimensions:          | 1"                                                                                                       |
| HF driver magnet:              | Ferrite                                                                                                  |
| HF driver brand:               | Custom-made                                                                                              |
| Amplifier:                     | Class D                                                                                                  |
| RMS:                           | 120 W                                                                                                    |
| Peak power:                    | 480 W                                                                                                    |
| Frequency range:               | 55 - 18,000 Hz                                                                                           |
| Max. SPL:                      | 115 dB                                                                                                   |
| Protection circuits:           | overvoltage, short circuit, limiters, DC                                                                 |
| Controls:                      | AUX / MP3 Switch, High, Low, Master Volume, Mic 2 Level, Mic 1 Level, CD / Tape IN Level, Echo           |
| Indicators:                    | power, charge/battery status                                                                             |
| Media player                   |                                                                                                          |
| Supported media:               | USB stick, Bluetooth, SD card                                                                            |
| Supported formats:             | MP3, WMA, WAV                                                                                            |
| Media player controls:         | Stop, Next track, Previous track, Repeat, Mode (Menu / Bluetooth / SD / USB), Play / Pause, Equalizer    |
| Media player display elements: | Lighted multifunctional LC display                                                                       |
| Line inputs:                   | 1                                                                                                        |
| Line input connectors:         | 3.5 mm Jack, 2 x RCA, 2 x XLR, 6.3 mm Jack                                                               |
| Mic inputs:                    | 2, XLR, 6.3 mm Jack                                                                                      |
| Wireless Unit                  |                                                                                                          |
| Radio Frequency Range          | Standard: 863 - 865 MHz<br>B5: 584 - 607 MHz<br>B6: 655 - 679 MHz                                        |
| Modulation Type                | analogue FM                                                                                              |
| Channels                       | 16                                                                                                       |
| Frequency range                | 50 - 17,000 Hz                                                                                           |
| Controllers                    | Power/Volume, Value Up, Value Down, ASC, MUTE-Level (squelch)                                            |
| Indicators                     | LED display, RF (LED), AF (LED)                                                                          |
| Connections                    | TNC for receiver antenna                                                                                 |
| RF Transmitter Power Output    | 10 mW                                                                                                    |
| Operating voltage:             | Switching Power Supply, 100 V - 120 V / 60 Hz, 220 V - 240 V AC / 50 Hz                                  |
| Rechargeable batteries:        | 12 V / 5 Ah                                                                                              |
| Cabinet material:              | PP black                                                                                                 |
| Cabinet construction:          | bass reflex                                                                                              |
| Dimensions (W x H x D):        | 415 mm x 525 mm x 328 mm                                                                                 |
| Weight:                        | 16.5 kg                                                                                                  |
| Other features:                | IR remote control for media player, carrying handle, 36 mm tripod flange, pull-out handle, castor wheels |

### AVAILABLE ACCESSORIES

**ROADBUDDY 10 PC** PROTECTIVE COVER FOR LD ROADBUDDY 10

### SPECIFICATIONS ROADJACK:

|                                |                                                                                                       |                                                                                                       |
|--------------------------------|-------------------------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------------|
| Art. No.:                      | LDRJ8                                                                                                 | LDRJ10                                                                                                |
| Product type:                  | Portable PA Speaker                                                                                   | Portable PA Speaker                                                                                   |
| Type:                          | active                                                                                                | active                                                                                                |
| Low/mid driver dimensions:     | 8"                                                                                                    | 10"                                                                                                   |
| Woofers magnet:                | Ferrite                                                                                               | Ferrite                                                                                               |
| Woofers brand:                 | Custom-made                                                                                           | Custom-made                                                                                           |
| HF driver dimensions:          | (broad band) 3"                                                                                       | (broad band) 3"                                                                                       |
| HF driver magnet:              | Ferrite                                                                                               | Ferrite                                                                                               |
| HF driver brand:               | Custom-made                                                                                           | Custom-made                                                                                           |
| Amplifier:                     | Class D                                                                                               | Class D                                                                                               |
| RMS:                           | 25 W                                                                                                  | 25 W                                                                                                  |
| Peak power:                    | 100 W                                                                                                 | 100 W                                                                                                 |
| Frequency range:               | 90 - 18,000 Hz                                                                                        | 65 - 18,000 Hz                                                                                        |
| Max. SPL:                      | 113 dB                                                                                                | 117 dB                                                                                                |
| Protection circuits:           | short circuit, over-current, overload protection                                                      | over-current, short circuit, overload protection                                                      |
| Controls:                      | Master Volume, Mic 2 Level, CD / Tape IN Level, high, low, Mic 1 Level, Echo, AUX / MP3 switch        | CD / Tape IN Level, low, Mic 1 Level, Mic 2 Level, Master Volume, AUX / MP3 switch, Echo, high        |
| Indicators:                    | Charge/battery status, Power                                                                          | Power, Charge/battery status                                                                          |
| Media player                   |                                                                                                       |                                                                                                       |
| Supported media:               | USB stick, Bluetooth, SD Card                                                                         | Bluetooth, SD Card, USB stick                                                                         |
| Supported formats:             | WAV, WMA file, MP3 file                                                                               | MP3 file, WMA file                                                                                    |
| Media player controls:         | Play / Pause, Repeat, Next Track, Mode (Menu / Bluetooth / SD / USB), Stop, Previous Track            | Play / Pause, Repeat, Next Track, Mode (Menu / Bluetooth / SD / USB), Stop, Previous Track            |
| Media player display elements: | Lighted multifunctional LC display                                                                    | Lighted multifunctional LC display                                                                    |
| Line inputs:                   | 1                                                                                                     | 1                                                                                                     |
| Line input connectors:         | 2 x RCA, 3.5 mm Jack                                                                                  | 2 x RCA, 3.5 mm Jack                                                                                  |
| Mic inputs:                    | 2, XLR / 6.3mm Jack Combo                                                                             | 2, XLR / 6.3mm Jack Combo                                                                             |
| Operating voltage:             | Switching Power Supply, 100 V - 120 V / 60 Hz, 220 V - 240 V AC / 50 Hz                               | Switching Power Supply, 100 V - 120 V / 60 Hz, 220 V - 240 V AC / 50 Hz                               |
| Rechargeable batteries:        | 12 V / 5 Ah                                                                                           | 12 V / 5 Ah                                                                                           |
| Cabinet material:              | 15 mm MDF                                                                                             | 15 mm MDF                                                                                             |
| Cabinet construction:          | vented                                                                                                | vented                                                                                                |
| Dimensions (W x H x D):        | 385 mm x 450 mm x 298 mm                                                                              | 415 mm x 525 mm x 328 mm                                                                              |
| Weight:                        | 13.8 kg                                                                                               | 16.2 kg                                                                                               |
| Other features:                | Extendable handle, transport handle, transport casters, IR remote for media player, stand mount 36 mm | Stand mount 36 mm, IR remote for media player, transport casters, transport handle, extendable handle |

### AVAILABLE ACCESSORIES

**ROADJACK 8 PC** PROTECTIVE COVERS FOR LDRJ8  
**ROADJACK 10 PC** PROTECTIVE COVERS FOR LDRJ10